

BATTERY SAFETY INFORMATION

Read and abide by **WARNING** notice below for your safety.

كترمالس ىلع هاندأ ريذحت راعش! مازتلالاو ءءارق.

Прочитайте и соблюдайте приведенное ниже предупреждение для вашей безопасности.

Leggere e rispettare le avvertenze riportate di seguito per la vostra sicurezza.

安全のため、下記の警告事項をよく読み、それに従ってください。

Lea y respete el siguiente aviso de advertencia para su seguridad.

안전을 위해 아래 경고주의 사항을 읽고 준수하십시오.

Lesen Sie sich zu Ihrer Sicherheit die unten stehenden Warnhinweise durch.



WARNING: LI-ION CELLS HAVE INHERENT RISKS IF MISUSED. IF MISUSED, CELL CAN EXPLODE CAUSING SEVERE BURN INJURY AND PROPERTY DAMAGE.

READ BELOW THOROUGHLY.



CELL = BATTERY

- **KEEP OUT OF REACH OF CHILDREN** and pets.
- **NEVER PUT IN FIRE**, oven, microwave, or heat over 100°C (212°F), as it can explode.
- **NEVER CARRY** or store **OUTSIDE** of its protective packaging or a **PROTECTIVE CELL CASE**.
- **NEVER PUT CELL IN POCKET**, purse, or anywhere **WITH METAL OBJECTS** including **COINS** and **KEYS**. Otherwise cell could short-circuit and **EXPLODE**.
- **NEVER PUT A DEVICE WITH CELL INSTALLED IN IT, IN YOUR POCKET**. As unlikely as it may be, the device could have a defect or internal damage not visible on the outside, that could short-circuit cell, resulting in catastrophic failure and **EXPLODE**.
- **NEVER USE IN A DEVICE THAT CAN EXCEED MAX CELL WATTAGE OR AMPERAGE** (listed on each cell and retail packaging). Otherwise if device fails to stop pulling power, the cell capabilities can be exceeded causing catastrophic failure and **EXPLODE**.
- **NEVER USE LOWER RESISTANCE (Ω) #** (listed on each cell and retail packaging). Otherwise cell capabilities can be exceeded causing catastrophic failure and **EXPLODE**.
- **NEVER USE CELL WITH DAMAGE TO ITS STRUCTURE OR OUTER PROTECTIVE LABEL** (also called "WRAP", "sleeve", "skin"). Damage may include: dent(s), tear(s), nick(s), puncture(s), corrosion, or any other abnormalities or undisclosed damage(s). Otherwise cell can short-circuit and **EXPLODE**. **ALWAYS INSPECT** cell **VISUALLY** and by **TOUCH** to **SEE/FEEL** for damage **BEFORE** each use. **USE ILLUSTRATION BELOW AS GUIDELINE**.
- **NEVER LEAVE UNATTENDED WHILE CHARGING**. As unlikely as it may be, a charger could malfunction or cause a short-circuit to cell, leading to catastrophic failure and **EXPLODE**.
- **WHEN CHARGING, REMOVE CELL(S) FROM CHARGER ONCE FULLY CHARGED** to ensure they are not at risk of exposure to any potential charger malfunction such as overcharging. **ONLY USE LI-ION CHARGER (3.6V & 3.7V)**
- **NEVER CHARGE HIGHER THAN MAX CHARGE VOLTAGE (V)** (typically 4.2V) or **DISCHARGE BELOW MAX VOLTAGE CUT-OFF (V)** (typically 2.5V) outlined inside this brochure. Otherwise this can cause irreversible damage or catastrophic failure and **EXPLODE**.
- **ALWAYS USE MATCHING CELLS IN MULTI-CELL DEVICES**. Differences in cell capacity can lead to overcharging or over-discharging cell. This can lead to catastrophic failure of one or more cells causing **EXPLOSION**.
- **IF USING A MULTI-CELL DEVICE, IT MUST HAVE A NON-CONDUCTIVE BARRIER** (typically plastic) **TO PREVENT ANY CELL FROM TOUCHING METAL** except for the very center of top and bottom of cell. Otherwise cell(s) could short-circuit and **EXPLODE**.
- **ALWAYS** use, connect, charge, and **OPERATE CELLS WITHIN THEIR CAPABILITIES** as listed on cell, packaging, and in this brochure, while adhering to the device's user manual.
- **IF USED IN A DEVICE THAT CAN OR DOES USE MORE THAN 50% of cell MAX AMPERAGE (A) OR MAX WATTAGE (W) LIMIT**, (listed on each cell and its packaging), **WE ADVISE TO REPLACE WITHIN 100 DAYS OF PURCHASE OR IMMEDIATELY IF DAMAGED**. Higher amperage or wattage levels accelerate cell aging and degradation, which decreases performance, capacity, and safety. * IF ONLY USED in device that cannot be set higher than 50% of either max amperage or max wattage, we advise replacing within 180 DAYS of purchase or immediately if damaged.
- **COMPLETELY READ** and follow the **WARNING** (⚠) section here, and listed on each cell, its retail packaging, and listed on the product detail pages at www.HohmTech.com.
- **VISIT** www.HohmTech.com for greater detail on safety & technical information.
- **SEARCH** www.YouTube.com for **"HOW TO REWRAP 18650"** and **"18650 EXPLOSIONS"** to understand and know the importance of using and maintaining li-ion cells properly. We do not advise any attempt at repair. We advise recycling and replacing cell.

KEEP YOUR WRAP 100% INTACT



GOOD BATTERY
This battery wrap is fully intact (no punctures/tears). If battery is the correct size & amp or wattage rating for your device, it is ready to use.

READY FOR USE



BAD BATTERY
This battery wrap has been damaged with puncture(s). This battery needs to be evaluated for either a new wrap installed on it before use or recycled.

DO NOT USE


BEFORE EACH USE, INSPECT FOR DAMAGE

(IE.: tear, nick, puncture, corrosion, hole, dent, or any other damage)

VISUALLY



and **BY TOUCH** TO SEE/FEEL FOR ANY DAMAGE



FEEL TOP AND ALL AROUND CELL TO DETECT ANY DAMAGE